

hohner

Esquema de ligação. Conector 21 pinos RC-Macho(Para Encoder Absoluto).

65XX-00G2-1024	65XX-11G2-0909	65XX-11G2-1206
Pino 1 = - 0V	Pino 1 = - 0V	Pino 1 = - 0V
Pino 2 = + Vdc	Pino 2 = + Vdc	Pino 2 = + Vdc
Pino 3 = Bit 01 - 2 ⁰	Pino 3 = Bit 01 - 2 ⁰	Pino 3 = Bit 01 - 2 ⁰
Pino 4 = Bit 02 - 2 ¹	Pino 4 = Bit 02 - 2 ¹	Pino 4 = Bit 02 - 2 ¹
Pino 5 = Bit 03 - 2 ²	Pino 5 = Bit 03 - 2 ²	Pino 5 = Bit 03 - 2 ²
Pino 6 = Bit 04 - 2 ³	Pino 6 = Bit 04 - 2 ³	Pino 6 = Bit 04 - 2 ³
Pino 7 = Bit 05 - 2 ⁴	Pino 7 = Bit 05 - 2 ⁴	Pino 7 = Bit 05 - 2 ⁴
Pino 8 = Bit 06 - 2 ⁵	Pino 8 = Bit 06 - 2 ⁵	Pino 8 = Bit 06 - 2 ⁵
Pino 9 = Bit 07 - 2 ⁶	Pino 9 = Bit 07 - 2 ⁶	Pino 9 = Bit 07 - 2 ⁶
Pino10 = Bit 08 - 2 ⁷	Pino10 = Bit 08 - 2 ⁷	Pino10 = Bit 08 - 2 ⁷
Pino11 = Bit 09 - 2 ⁸	Pino11 = Bit 09 - 2 ⁸	Pino11 = Bit 09 - 2 ⁸
Pino12 = Bit 09 - 2 ⁹	Pino12 = Bit 10 - 2 ⁹	Pino12 = Bit 10 - 2 ⁹
Pino13 = N/C	Pino13 = Bit 11 - 2 ¹⁰	Pino13 = Bit 11 - 2 ¹⁰
Pino14 = N/C	Pino14 = Bit 12 - 2 ¹¹	Pino14 = Bit 12 - 2 ¹¹
Pino15 = N/C	Pino15 = Bit 13 - 2 ¹²	Pino15 = Bit 13 - 2 ¹²
Pino16 = N/C	Pino16 = Bit 14 - 2 ¹³	Pino16 = Bit 14 - 2 ¹³
Pino17 = N/C	Pino17 = Bit 15 - 2 ¹⁴	Pino17 = Bit 15 - 2 ¹⁴
Pino18 = N/C	Pino18 = Bit 16 - 2 ¹⁵	Pino18 = Bit 16 - 2 ¹⁵
Pino19 = N/C	Pino19 = Bit 17 - 2 ¹⁶	Pino19 = Bit 17 - 2 ¹⁶
Pino20 = N/C	Pino20 = Bit 18 - 2 ¹⁷	Pino20 = Bit 18 - 2 ¹⁷
Pino21 = CW/CCW	Pino21 = CW/CCW	Pino21 = CW/CCW

65XX-11G2-1006

Pino 1 = - 0V
Pino 2 = + Vdc
Pino 3 = Bit 01 - 2^0
Pino 4 = Bit 02 - 2^1
Pino 5 = Bit 03 - 2^2
Pino 6 = Bit 04 - 2^3
Pino 7 = Bit 05 - 2^4
Pino 8 = Bit 06 - 2^5
Pino 9 = Bit 07 - 2^6
Pino10 = Bit 08 - 2^7
Pino11 = Bit 09 - 2^8
Pino12 = Bit 09 - 2^9
Pino13 = Bit 11 - 2^{10}
Pino14 = Bit 12 - 2^{11}
Pino15 = Bit 13 - 2^{12}
Pino16 = Bit 14 - 2^{13}
Pino17 = Bit 15 - 2^{14}
Pino18 = Bit 16 - 2^{15}
Pino19 = N/C
Pino20 = N/C
Pino21 = CW/CCW

65XX-11G1-1105

Pino 1 = - 0V
Pino 2 = + Vdc
Pino 3 = Bit 01 - 2^0
Pino 4 = Bit 02 - 2^1
Pino 5 = Bit 03 - 2^2
Pino 6 = Bit 04 - 2^3
Pino 7 = Bit 05 - 2^4
Pino 8 = Bit 06 - 2^5
Pino 9 = Bit 07 - 2^6
Pino10 = Bit 08 - 2^7
Pino11 = Bit 09 - 2^8
Pino12 = Bit 10 - 2^9
Pino13 = Bit 11 - 2^{10}
Pino14 = Bit 12 - 2^{11}
Pino15 = Bit 13 - 2^{12}
Pino16 = Bit 14 - 2^{13}
Pino17 = Bit 15 - 2^{14}
Pino18 = Bit 16 - 2^{15}
Pino19 = N/C
Pino20 = N/C
Pino21 = CW/CCW

65XX-11G2-1003

Pino 1 = - 0V
Pino 2 = + Vdc
Pino 3 = Bit 01 - 2^0
Pino 4 = Bit 02 - 2^1
Pino 5 = Bit 03 - 2^2
Pino 6 = Bit 04 - 2^3
Pino 7 = Bit 05 - 2^4
Pino 8 = Bit 06 - 2^5
Pino 9 = Bit 07 - 2^6
Pino10 = Bit 08 - 2^7
Pino11 = Bit 09 - 2^8
Pino12 = Bit 10 - 2^9
Pino13 = Bit 11 - 2^{10}
Pino14 = Bit 12 - 2^{11}
Pino15 = Bit 13 - 2^{12}
Pino16 = N/C
Pino17 = N/C
Pino18 = N/C
Pino19 = N/C
Pino20 = N/C
Pino21 = CW/CCW